

WiiM CI MOD S

An audiophile-grade streamer featuring an AKM AK4493SEQ DAC, supporting Hi-Res Audio up to 24-bit/192kHz, and offering versatile connectivity for various installation needs.

Feature	Description
Power Input	USB Type-C, requires 5V, 1.5A or higher Bundled adapter: 5V, 2A
Digital Audio Output	Bit-perfect output, up to 192 kHz, 24-bit with digital optical or coaxial output
Network	802.11 b/g/n/ac 2.4 GHz and 5 GHz dual bands Wi-Fi 10/100M Ethernet
Bluetooth	Bluetooth 5.1
Audio Input	1 x Analog RCA Line input, 1 x SPDIF in Optical, up to 192kHz/24-bit
Audio Output	1 x Analog RCA Line output, 1 x Digital optical (SPDIF) output, 1 x Digital Coaxial output, up to 192kHz/32-bit
DAC	AKM AK4493SEQ
Trigger Out	3.5mm Trigger out
SNR	120 dB
THD+N	0.00032% (-110 dB)
Audio Codec	MP3, AAC, ALAC, APE, FLAC, WAV, WMA, OGG
Equalizer	24 preset EQ settings for different music genres 10-band graphic EQ that can adjust to optimize sound performance for every audio source (Line in, BT or Network) 10-band parametric R/L EQ that can adjust to optimize the sound performance based on your room characteristics, allowing more fine granular adjustment Bass management Built-in Room Correction
Protocol	Chromecast Audio, DLNA, Spotify Connect, TIDAL Connect, Amazon Music Casting, Qplay 2.0, Roon
Streaming Services in WiiM Home App	Spotify, Amazon Music, Deezer, TuneIn, Tidal, Qobuz, SoundCloud, Pandora, iHeartRadio, vTuner, Napster, SoundMachine, BBC Radio, Calm Radio, Radio Paradise, Sound Track Your Brand, more to come.
Supported Control Platforms	Control 4, RTI, URC, Josh.ai
Buttons	Touch buttons: Play/Pause/Setup, Volume +, Volume -, Preset
Weight	11.6 oz (330g)
Dimensions	(L) 5.5 x (W) 5.5 x (H) 1.6 (Inch) / (L) 140 x (W) 140 x (H) 42 (mm)
What's in the box	WiiM CI MOD S (1), Optical cable (1), Stereo RCA cable (1), Type C cable (1), Adapter (1), Screws (3)

WiiM CI MOD A80

A versatile streaming amplifier that combines an ESS 9018K2M DAC with a TI TPA3255 Class-D amplifier, delivering 60W per channel at 8 ohms, and supporting the latest Wi-Fi 6E and Bluetooth 5.3 technologies.

Feature	Description
Power Input	100-240V AC
Network	Wi-Fi 6E, 802.11 b/g/n/ax 2.4 GHz, 5 GHz, and 6 GHz triple bands
Bluetooth	Bluetooth 5.3 with BLE and BT supports both A2DP receiver and transmitter, AVRCP, HID, works with the WiiM Voice Remote
Audio Input	Analog (RCA), Digital Optical Port, HDMI ARC, up to 24-bit/192 kHz
Audio Output	Banana (x2), Subwoofer out
USB	USB Host: Connects to USB disk for local music playback USB Audio: Supports two-channel USB audio output
Amplifier	TI TPA 3255 Class-D digital amplifier
Power	60 W/channel (8 ohms), 120 W/channel (4 ohms)
DAC	Highest Performance 32-bit ESS Sabre 9018K2M
SNR	108 dB
THD+N	- 95 dB, 5W @ 8 Ohms
Audio Codec	MP3, AAC, ALAC, APE, FLAC, WAV, WMA, OGG
Equalizer	24 preset EQ settings for different music genres 10-band graphic EQ that can adjust to optimize sound performance for every audio source (Line in, BT or Network) 10-band parametric R/L EQ that can adjust to optimize the sound performance based on your room characteristics, allowing more fine granular adjustment Bass management Built-In Room Correction
Protocol	Chromecast Audio, DLNA, Spotify Connect, TIDAL Connect, Amazon Music Casting, Qplay 2.0, Roon
Streaming Services in WiiM Home App	Spotify, Amazon Music, Deezer, Tunein, Tidal, Qobuz, SoundCloud, Pandora, iHeartRadio, vTuner, Napster, Sound machine, Sound Track Your Brand, and more to come
Supported Control Platforms	Control 4, RTI, URC, Josh.ai
Weight	68.26 oz (1.935 kg)
Dimension	(L) 7.48 x (W) 7.48 x (H) 2.52 (Inch) / (L) 190 x (W) 190 x (H) 64 (mm)
What's in the box	WiiM CI MOD A80 (1), Optical cable (1), Stereo RCA cable (1), HDMI cable (1), Power cable (1), Screws (7), Mounting brackets (2)